

Installation Brief for Linksys SPA2100

SPA2100 (Analogue Telephone Adaptor)

Please read all instructions carefully

1. Switch off your modem/router.
2. Connect one end of an Ethernet network cable (included) to the INTERNET port of the SPA2100 and the other end to a spare Ethernet port on your cable/DSL modem.
3. Connect the power lead to the 5V DC power connection on the back of the SPA-2100. Connect the power plug to a power point.
4. Connect an analogue telephone handset to the RJ11 port marked "Phone 1" or "Phone 2" of the SPA2100 (as indicated in the picture below) for a first or second NexVoice service respectively.
- 5.



Do not connect the "Phone" port of the SPA-2100 into your telephone wall socket or you will cause the ATA to malfunction.

6. Power on the device.
7. In the case if you wish to use your PC to gain access to the Internet, connect the "LAN/Ethernet" port of your PC/Laptop to the Ethernet port of the SPA2100. Refer to the Installation Guideline for Certified Telephone Adaptors for different optional configurations.
8. When the Internet connection is re-established, the SPA2100 should obtain an IP address and automatically download a configuration file from the NexVoice network. After 30 seconds the configuration should be complete.
9. The telephone connected to the SPA2100 should have a dial tone and you are ready to make cheaper telephone calls.



If you require any further assistance, please call Nextep Broadband Customer Support Help Desk on **1800 639 837**.